

LIGHTING BATTERY



Lithium-NCM 30V 28.4Ah



Double Charger 30V 28.4Ah



Lithium-NCM 30V 14.2Ah



Double Charger 30V 14.2Ah

Lithium-NCM 30V 28.4Ah

■ SPECIFICATIONS

Identity No.	A03028L2
Capacity	28,000mAh (Min.) 28,400mAh (Typical)
Voltage	28.8V - 33.6V
Charging Voltage	33.6V ± 0.3V
Max.Charging Current	6,000mA
Max.Discharging Current	32A
Dimensions (mm)	300 x 265 x 90
Weight	7.0 kg

Double Charger 30V 28.4Ah

■ SPECIFICATIONS

Identity No.	A0306WLC
Max. Output	33.6V / 6A
Dimensions (mm)	260 x 220 x 110
Weight	2.9 kg

Lithium-NCM 30V 14.2Ah

■ SPECIFICATIONS




Identity No.	A03014L2
Capacity	14,000mAh (Min.) 14,200mAh (Typical)
Voltage	28.8V - 33.6V
Charging Voltage	33.6V ± 0.3V
Max.Charging Current	5,000mA
Max.Discharging Current	16A
Dimensions (mm)	240 x 210 x 90
Weight	3.9 kg

Double Charger 30V 14.2Ah

■ SPECIFICATIONS

Identity No.	A0305WLC
Max. Output	33.6V / 3A
Dimensions (mm)	185 x 205 x 100
Weight	1.7 kg

BATTERY OPERATED


+

+


Daylight Par 800W

800W/575W AC/DC Ballast

30V 28.4Ah Battery

Daylight Par 800W DC

■ SET CONTENTS

- (1) Lamphead with Bulb
- (1) 800W/575W AC/DC Ballast
- (1) Lamphead to Ballast Cable

With (2) 30V 28.4Ah Battery


- (1) DC Y-Cable

Running Time : 110mins

With (1) 30V 28.4Ah Battery


- (1) DC Cable

Running Time : 50mins





Daylight Par 575W

or



Daylight Fresnel 575W

+

+


800W/575W AC/DC Ballast




30V 28.4Ah Battery

Daylight Par 575W DC Daylight Fresnel 575W DC

■ SET CONTENTS

- (1) Lamphead with Bulb
- (1) 800W/575W AC/DC Ballast
- (1) Lamphead to Ballast Cable
- (1) 30V 28.4Ah Battery
- (1) DC Cable

Running Time : 90mins


+

+


Daylight Par 400W Mini

400W/200W AC/DC Ballast


30V 14.2Ah Battery

Daylight Par 400W Mini DC

■ SET CONTENTS


- (1) Lamphead with Bulb
- (1) 400W/200W AC/DC Ballast
- (1) Lamphead to Ballast Cable
- (1) 30V 14.2Ah Battery
- (1) DC Cable

Running Time : 45mins




Daylight Par 200W

or





Daylight Par 200W Mini

or



Daylight Fresnel 200W

+

+


200W AC/DC Ballast

30V 14.2Ah Battery

Daylight Par 200W DC Daylight Par 200W Mini DC Daylight Fresnel 200W DC

■ SET CONTENTS

- (1) Lamphead with Bulb
- (1) 200W AC/DC Ballast
- (1) Lamphead to Ballast Cable
- (1) 30V 14.2Ah Battery
- (1) DC Cable

Running Time : 105mins

BATTERY OPERATED

Flo-Box 2 Bank 4 ft
Flo-Box 2 Bank 2 ft

+ 30V 14.2Ah Battery

2 Bank AC/DC Ballast

Flo-Box 2 Bank 4 ft DC Flo-Box 2 Bank 2 ft DC

■ SET CONTENTS

- (1) Lamphead with Tubes
- (1) 2 Bank AC/DC Ballast
- (1) Lamphead to Ballast Cable
- (1) 30V 14.2Ah Battery
- (1) DC Cable

Running Time : 2 Bank 4 ft - 130mins
2 Bank 2 ft - 230mins

Flo-Box 4 Bank 4 ft
Flo-Box 4 Bank 2 ft

+ 30V 14.2Ah Battery

4 Bank AC/DC Ballast

Flo-Box 4 Bank 4 ft DC Flo-Box 4 Bank 2 ft DC

■ SET CONTENTS

- (1) Lamphead with Tubes
- (1) 4 Bank AC/DC Ballast
- (1) Lamphead to Ballast Cable
- (1) 30V 14.2Ah Battery
- (1) DC Cable

Running Time : 4 Bank 4 ft - 65mins
4 Bank 2 ft - 115mins