

Manufacture Name: Film Gear Int. Ltd

Manufacture ID: 0x4142

Product Name: Aurora RGB 200 Aurora RGB 400 Aurora V2 RGB 220 Aurora V2 RGB 450

Model ID: 0x0202 0x0201 0x0211 0x0212

Version: V1.74 or above

DMX Mode: Mode 1 : 8-bit functional setting of CCT and RGBWW
Mode 2 : 8-bit functional setting of CCT
Mode 3 : 8-bit functional setting of CCT and HSI
Mode 4 : 8-bit functional setting of RGBWW
Mode 5 : 8-bit functional setting of H.S.I.
Mode 6 : 16-bit functional setting of CCT and RGBWW
Mode 7 : 16-bit functional setting of CCT
Mode 8 : 16-bit functional setting of CCT and H.S.I.
Mode 9 : 16-bit functional setting of RGBWW
Mode 10 : 16-bit functional setting of H.S.I.
Mode 11 : Coarse/Fine Tuning of CCT and RGBWW
Mode 12 : Coarse/Fine Tuning of CCT
Mode 13 : Coarse/Fine Tuning of CCT and H.S.I
Mode 14 : Coarse/Fine Tuning of RGBWW
Mode 15 : Coarse/Fine Tuning of H.S.I.
Mode 16 : GEL, 8 bit resolution per function, base channels
Mode 17 : GEL, 16 bit resolution per function, base channels
Mode 18 : x,y Coordinates, 8 bit resolution per function
Mode 19 : x,y Coordinates 16 bit resolution per function
Mode 20 : Effects, 8 bit resolution per function
Mode 21 : Effects, 16 bit resolution per function
Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function
Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 1 : 8-bit functional setting of CCT and RGBWW

DMX Channel	Value	Percent	Function
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Color Temp. (2700K~10000K)
3	Green / Magenta Adjustment		
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
	245~255	97~100	full plus green
4	0 – 255	0 – 100	Color Change Coefficient White --> Color
5	0 – 255	0 – 100	Adjust Red Color intensity
6	0 – 255	0 – 100	Adjust Green Color intensity
7	0 – 255	0 – 100	Adjust Blue Color intensity
8	0 – 255	0 – 100	Adjust Warm White Color intensity
9	0 – 255	0 – 100	Adjust Cold White Color intensity
10	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
11 ~ 13			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 2 : 8-bit functional setting of CCT

DMX Channel	Value	Percent	Function
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Color Temp. (2700K~10000K)
3	Green / Magenta Adjustment		
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
	245~255	97~100	full plus green
4	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
5 ~ 7			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 3 : 8-bit functional setting of CCT and HSI

DMX Channel	Value	Percent	Function
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Color Temp. (2700K~10000K)
3	Green / Magenta Adjustment		
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
	245~255	97~100	full plus green
4	0 – 255	0 – 100	Color Change Coefficient White --> Color
5	0 – 255	0 – 100	Adjust HUE (0~359)
6	0 – 255	0 – 100	Adjust Saturation (0~100%)
7	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
8 ~ 10			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 4 : 8-bit functional setting of RGBWW

DMX Channel	Value	Percent	Function
1	Master Intensity		
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Adjust Red Color intensity
3	0 – 255	0 – 100	Adjust Green Color intensity
4	0 – 255	0 – 100	Adjust Blue Color intensity
5	0 – 255	0 – 100	Adjust Warm White Color intensity
6	0 – 255	0 – 100	Adjust Cold White Color intensity
7	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
8 ~ 10			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 5 : 8-bit functional setting of H.S.I.

DMX Channel	Value	Percent	Function
1	Master Intensity		
	0 - 255	0 - 100	0 % (closed) → 100% (open)
2	0 - 255	0 - 100	Adjust HUE (0~359)
3	0 - 255	0 - 100	Adjust Saturation (0~100%)
4	Fan control		
	0 - 9	0 - 3	As Fixture Setting
	10 - 49	4 - 19	Quiet Mode
	50 - 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 - 175	60 - 68	Full Speed
	176 - 200	69 - 78	Full Speed but Limited Output 80%
	201 - 225	79 - 88	Full Speed but Limited Output 60%
	226 - 249	89 - 97	Full Speed but Limited Output 40%
250 - 255	98 - 100	Reserved for future use	
5 ~ 7			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 6 : 16-bit functional setting of CCT and RGBWW

DMX Channel	Value	Percent	Function
1 (Hi)			Master Intensity
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (hi)	0 –65535	0 – 100	Color Temp. (2700K~10000K)
4 (lo)			
Green / Magenta Adjustment			
5 (hi)	0~5000	0~7	neutral / no effect
	5001~10000	8~15	full minus green
	10001~29999	16~46	-99% --> -1%
	30000~40000	47~61	neutral / no effect
	40001~59999	62~92	1% --> 99%
	60000~65535	93~100	full plus green
7 (hi)	0 –65535	0 – 100	Color Change Coefficient White --> Color
8 (lo)			
9 (hi)	0 –65535	0 – 100	Adjust Red Color intensity
10 (lo)			
11 (hi)	0 –65535	0 – 100	Adjust Green Color intensity
12 (lo)			
13 (hi)	0 –65535	0 – 100	Adjust Blue Color intensity
14 (lo)			
15 (hi)	0 –65535	0 – 100	Adjust Warm White Color intensity
16 (lo)			
17 (hi)	0 –65535	0 – 100	Adjust Cold White Color intensity
18 (lo)			

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 6 : 16-bit functional setting of CCT and RGBWW

DMX Channel	Value	Percent	Function
19			Fan control
	0 - 9	0 - 3	As Fixture Setting
	10 - 49	4 - 19	Quiet Mode
	50 - 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 - 175	60 - 68	Full Speed
	176 - 200	69 - 78	Full Speed but Limited Output 80%
	201 - 225	79 - 88	Full Speed but Limited Output 60%
	226 - 249	89 - 97	Full Speed but Limited Output 40%
	250 - 255	98 - 100	Reserved for future use
20~21			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 7 : 16-bit functional setting of CCT

DMX Channel	Value	Percent	Function
1 (Hi)			Master Intensity
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (hi)	0 –65535	0 – 100	Color Temp. (2700K~10000K)
4 (lo)			
Green / Magenta Adjustment			
5 (hi) 6 (lo)	0~5000	0~7	neutral / no effect
	5001~10000	8~15	full minus green
	10001~29999	16~46	-99% --> -1%
	30000~40000	47~61	neutral / no effect
	40001~59999	62~92	1% --> 99%
	60000~65535	93~100	full plus green
Fan control			
7	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
8~10			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 8 : 16-bit functional setting of CCT and H.S.I.

DMX Channel	Value	Percent	Function
1 (Hi)			Master Intensity
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (hi)	0 –65535	0 – 100	Color Temp. (2700K~10000K)
4 (lo)			
Green / Magenta Adjustment			
5 (hi) 6 (lo)	0~5000	0~7	neutral / no effect
	5001~10000	8~15	full minus green
	10001~29999	16~46	-99% --> -1%
	30000~40000	47~61	neutral / no effect
	40001~59999	62~92	1% --> 99%
	60000~65535	93~100	full plus green
7 (hi)	0 –65535	0 – 100	Color Change Coefficient
8 (lo)			White --> Color
9 (hi)	0 –65535	0 – 100	Adjust HUE (0~359)
10 (lo)			
11 (hi)	0 –65535	0 – 100	Adjust Saturation (0~100%)
12 (lo)			
Fan control			
13	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
14~16			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 9 : 16-bit functional setting of RGBWW

DMX Channel	Value	Percent	Function
1 (Hi)			Master Intensity
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (hi)	0 –65535	0 – 100	Adjust Red Color intensity
4 (lo)			
5 (hi)	0 –65535	0 – 100	Adjust Green Color intensity
6 (lo)			
7 (hi)	0 –65535	0 – 100	Adjust Blue Color intensity
8 (lo)			
9 (hi)	0 –65535	0 – 100	Adjust Warm White Color intensity
10 (lo)			
11 (hi)	0 –65535	0 – 100	Adjust Cold White Color intensity
12 (lo)			
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
14~16			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 10 : 16-bit functional setting of H.S.I.

DMX Channel	Value	Percent	Function
1 (Hi)			Master Intensity
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (hi)	0 –65535	0 – 100	Adjust HUE (0~359)
4 (lo)			
5 (hi)	0 –65535	0 – 100	Adjust Saturation (0~100%)
6 (lo)			
7	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
8~10			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 11 : Coarse/Fine Tuning of CCT and RGBWW

DMX Channel	Value	Percent	Function
Master Intensity			
1	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Fine Tune intensity (10%)
Adjust Color Temp.			
3	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	0 – 255	0 – 100	Fine Tune Color Temp.
Green / Magenta Adjustment			
5	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
	245~255	97~100	full plus green
6	0 – 255	0 – 100	Color Change Coefficient White --> Color
Adjust Red			
7	0 – 255	0 – 100	Adjust Red (0~100%)
8	0 – 255	0 – 100	Fine Tune Red (10%)
Adjust Green			
9	0 – 255	0 – 100	Adjust Green (0~100%)
10	0 – 255	0 – 100	Fine Tune Green (10%)
Adjust Blue			
11	0 – 255	0 – 100	Adjust Blue (0~100%)
12	0 – 255	0 – 100	Fine Tune Blue (10%)
Adjust Warm White			
13	0 – 255	0 – 100	Adjust Warm White (0~100%)
14	0 – 255	0 – 100	Fine Tune Warm White (10%)
Adjust Cold White			
15	0 – 255	0 – 100	Adjust Cold White (0~100%)
16	0 – 255	0 – 100	Fine Tune Cold White (10%)

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 11 : Coarse/Fine Tuning of CCT and RGBWW

DMX Channel	Value	Percent	Function
17			Fan control
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
18 ~ 20			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 12 : Coarse/Fine Tuning of CCT

DMX Channel	Value	Percent	Function
1	Master Intensity		
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Fine Tune intensity (10%)
3	Adjust Color Temp.		
	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	0 – 255	0 – 100	Fine Tune Color Temp.
5	Green / Magenta Adjustment		
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
	245~255	97~100	full plus green
6	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
7 ~ 9			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 13 : Coarse/Fine Tuning of CCT and H.S.I

DMX Channel	Value	Percent	Function
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Fine Tune intensity (10%)
3			Adjust Color Temp.
	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	0 – 255	0 – 100	Fine Tune Color Temp.
5			Green / Magenta Adjustment
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
	245~255	97~100	full plus green
6	0 – 255	0 – 100	Color Change Coefficient White --> Color
7			Adjust HUE
	0 – 255	0 – 100	Adjust HUE (0~359)
8	0 – 255	0 – 100	Fine Tune HUE (10%)
9			Adjust Saturation
	0 – 255	0 – 100	Adjust Saturation (0~100%)
10	0 – 255	0 – 100	Fine Tune Saturation (10%)
11			Fan control
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
12 ~ 14			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 14 : Coarse/Fine Tuning of RGBWW

DMX Channel	Value	Percent	Function
Master Intensity			
1	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Fine Tune intensity (10%)
Adjust Red			
3	0 – 255	0 – 100	Adjust Red (0~100%)
4	0 – 255	0 – 100	Fine Tune Red (10%)
Adjust Green			
5	0 – 255	0 – 100	Adjust Green (0~100%)
6	0 – 255	0 – 100	Fine Tune Green (10%)
Adjust Blue			
7	0 – 255	0 – 100	Adjust Blue (0~100%)
8	0 – 255	0 – 100	Fine Tune Blue (10%)
Adjust Warm White			
9	0 – 255	0 – 100	Adjust Warm White (0~100%)
10	0 – 255	0 – 100	Fine Tune Warm White (10%)
Adjust Cold White			
11	0 – 255	0 – 100	Adjust Cold White (0~100%)
12	0 – 255	0 – 100	Fine Tune Cold White (10%)
Fan control			
13	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
14 ~ 16			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 15 : Coarse/Fine Tuning of H.S.I.

DMX Channel	Value	Percent	Function
1	Master Intensity		
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Fine Tune intensity (10%)
3	Adjust HUE		
	0 – 255	0 – 100	Adjust HUE (0~359)
4	0 – 255	0 – 100	Fine Tune HUE (10%)
5	Adjust Saturation		
	0 – 255	0 – 100	Adjust Saturation (0~100%)
6	0 – 255	0 – 100	Fine Tune Saturation (10%)
7	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
8 ~ 10			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
Aurora V1 400C 0x0201
Aurora V2 220C 0x0211
Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
1	0 – 255	0 – 100	Master Intensity
2	Gel 1, CCT Selection		
	0 – 127	0 – 50	3.200 K
	128 – 255	51 – 100	5.600 K
3	Gel 1: Filter Class		
	0 – 12	0 – 4	CTB under Color Correction
	13 – 25	5 – 9	CTO under Color Correction
	26 – 38	10 – 14	CTS under Color Correction
	39 – 50	15 – 19	+/- Green under Color Correction
	51 – 61	20 – 24	Misc under Color Correction
	62 – 127	25 – 49	Reserved
	128 – 140	50 – 54	Red under Color Filter
	141 – 152	55 – 59	Orange under Color Filter
	153 – 165	60 – 64	Yellow under Color Filter
	166 – 178	65 – 69	Green under Color Filter
	179 – 191	70 – 74	Blue under Color Filter
	192 – 203	75 – 79	Purple under Color Filter
204 – 255	80 – 100	Reserved	
4	0 – 255	0 – 100	Gel 1: Filter Code

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
5	0 – 255	0 – 100	Cross Fade from Gel 1 to Gel2
6	Gel 2, CCT Selection		
	0 – 127	0 – 50	3.200 K
	128 – 255	51 – 100	5.600 K
7	Gel 2: Filter Class		
	0 – 12	0 – 4	CTB under Color Correction
	13 – 25	5 – 9	CTO under Color Correction
	26 – 38	10 – 14	CTS under Color Correction
	39 – 50	15 – 19	+/- Green under Color Correction
	51 – 61	20 – 24	Misc under Color Correction
	62 – 127	25 – 49	Reserved
	128 – 140	50 – 54	Red under Color Filter
	141 – 152	55 – 59	Orange under Color Filter
	153 – 165	60 – 64	Yellow under Color Filter
	166 – 178	65 – 69	Green under Color Filter
	179 – 191	70 – 74	Blue under Color Filter
	192 – 203	75 – 79	Purple under Color Filter
	204 – 255	80 – 100	Reserved
8	0 – 255	0 – 100	Gel 2: Filter Code
9	Transition Type		
	0~41	0~16	Direct
	42~83	17~32	Through White Point
	84~125	33~49	Through Black Point
	126~167	50~65	Dissolve (future development plan)
	168~209	66~82	Over White Point (future development plan)
210~255	83~100	Under White point (future development plan)	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
10	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
11~13	0 – 255	0 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for CTB under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 0 ~ 12)	0 - 4	1	RCC3220	CTB Double
	5 - 7	2	RCC3202	CTB Full
	8 - 10	3	RCC3203	CTB 3/4
	11 - 12	4	RCC3204	CTB 1/2
	13 - 15	5	RCC3208	CTB 1/4
8 (for Gel 2) (Preset CH7: 0 ~ 12)	16 - 17	6	RCC3216	CTB 1/8
	18 - 20	7	LCC0283	CTB 1-1/2
	21 - 22	8	LCC0201	CTB Full
	23 - 25	9	LCC0281	CTB 3/4
	26 - 27	10	LCC0202	CTB 1/2
	28 - 30	11	LCC0203	CTB 1/4
	31 - 33	12	LCC0218	CTB 1/8
	34 - 255	13 - 100		Reserved for future use

Filter code for CTO under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 13 ~ 25)	0 - 4	1	RCC3407	CTO Full
	5 - 7	2	RCC3411	CTO 3/4
	8 - 10	3	RCC3408	CTO 1/2
	11 - 12	4	RCC3409	CTO 1/4
	13 - 15	5	RCC3410	CTO 1/8
8 (for Gel 2) (Preset CH7: 13 ~ 25)	16 - 17	6	LCC0286	CTO 1-1/2
	18 - 20	7	LCC0208	CTO Full+6ND
	21 - 22	8	LCC0207	CTO Full+3ND
	23 - 25	9	LCC0206	CTO 1/4
	26 - 27	10	LCC0287	CTO Double
	28 - 30	11	LCC0204	CTO Full
	31 - 33	12	LCC0285	CTO 3/4
	34 - 35	13	LCC0205	CTO 1/2
	36 - 38	14	LCC0223	CTO 1/8
	39 - 255	15 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for CTS under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 26 ~ 38	0 - 4	1	RCC3441	CTS Full
	5 - 7	2	RCC3442	CTS 1/2
	8 - 10	3	RCC3443	CTS 1/4
	11 - 12	4	RCC3444	CTS 1/8
	13 - 15	5	LCC0441	CTS Full
8 (for Gel 2) (Preset CH7: 26 ~ 38	16 - 17	6	LCC0442	CTS 1/2
	18 - 20	7	LCC0443	CTS 1/4
	21 - 22	8	LCC0444	CTS 1/8
	23 - 255	9 - 100		Reserved for future use

Filter code for +/-Green under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 39 ~ 50	0 - 4	1	RCC3304	Plusgreen Full
	5 - 7	2	RCC3315	Plusgreen 1/2
	8 - 10	3	RCC3316	Plusgreen 1/4
	11 - 12	4	RCC3317	Plusgreen 1/8
	13 - 15	5	RCC3308	Minusgreen Full
8 (for Gel 2) (Preset CH7: 39 ~ 50	16 - 17	6	RCC3309	Minusgreen 3/4
	18 - 20	7	RCC3313	Minusgreen 1/2
	21 - 22	8	RCC3314	Minusgreen 1/4
	23 - 25	9	RCC3318	Minusgreen 1/8
	26 - 27	10	LCC0244	L.Plus Green
	28 - 30	11	LCC0245	Plus Green 1/2
	31 - 33	12	LCC0246	Plus Green 1/4
	34 - 35	13	LCC0278	Plus Green 1/8
	36 - 38	14	LCC0247	L. Minus Green
	39 - 40	15	LCC0248	Minus Green 1/2
	41 - 43	16	LCC0249	Minus Green 1/4
	44 - 45	17	LCC0279	Minus Green 1/8
	46 - 255	18 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Misc under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 51 ~ 61	0 - 4	1	RCC3102	Tough MT2
	5 - 7	2	RCC3106	Tough MTY
	8 - 10	3	RCC3107	Tough Y-1
	11 - 12	4	RCC3134	Tough MT
	13 - 15	5	RCC3150	Industrial Vapor
8 (for Gel 2) (Preset CH7: 51 ~ 61	16 - 17	6	RCC3152	Urban Vapor
	18 - 20	7	RCC3310	Fluoro Ffilter
	21 - 22	8	LCC0212	LCT Yellow (Y1)
	23 - 25	9	LCC0213	White Flame Green
	26 - 27	10	LCC0219	Fluo Green
	28 - 30	11	LCC0230	S.Corr LCT Yellow
	31 - 33	12	LCC0232	S Corr WF Green
	34 - 35	13	LCC0236	HMI (to Tungsten)
	36 - 38	14	LCC0237	CID (to Tungsten)
	39 - 40	15	LCC0238	CSI (to Tungsten)
	41 - 43	16	LCC0241	L.Fluro 5700K
	44 - 45	17	LCC0242	L.Fluro 4300K
	46 - 48	18	LCC0243	L.Fluro 3600K
	49 - 255	19 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Red

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 128 ~ 140)	0 - 4	1	RCA4615	Red 15
	5 - 7	2	RCA4630	Red 30
	8 - 10	3	RCA4660	Red 60
	11 - 12	4	RCA4690	Red 90
8 (for Gel 2) (Preset CH7: 128 ~ 140)	13 - 15	5	RCA4815	Pink 15
	16 - 17	6	RCA4830	Pink 30
	18 - 20	7	RCA4860	Pink 60
	21 - 22	8	RCA4890	Pink 90
	23 - 25	9	RCC3102	Tough MT2
	26 - 27	10	RCL0021	Golden Amber
	28 - 30	11	RCL0026	Light Red
	31 - 33	12	RCL0033	No Color Pink
	34 - 35	13	RCL0034	Flesh Pink
	36 - 38	14	RCL0041	Salmon
	39 - 40	15	RCL0042	Deep Salmon
	41 - 43	16	RCL0044	Middle Rose
	44 - 45	17	RCL0318	Mayan Sun
	46 - 48	18	RCL0321	Soft Golden Amber
	49 - 50	19	RCL0325	Henna Sky
	51 - 53	20	RCL0333	Blush Pink
	54 - 55	21	RSS2001	VS-Red
	56 - 58	22	L700748	Seedy Pink
	59 - 61	23	L700779	Bastard Pink
	62 - 63	24	L700781	Terry Red
	64 - 66	25	L700790	Moroccan Pink
	67 - 68	26	L700794	Pretty n Pink
	69 - 71	27	L700795	Magical Magenta
	72 - 73	28	LCF0002	Rose Pink
	74 - 76	29	LCF0008	Dark Salmon
	77 - 78	30	LCF0019	Fire
	79 - 81	31	LCF0024	Scarlet
	82 - 84	32	LCF0025	Sunset Red
	85 - 86	33	LCF0026	Bright Red
	87 - 89	34	LCF0035	Light Pink

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
	90 – 91	35	LCF0036 Med. Pink
	92 – 94	36	LCF0046 Dark Magenta
	95 – 96	37	LCF0048 Rose Purple
	97 – 99	38	LCF0106 Primary Red
	100 – 101	39	LCF0107 Light Rose
	102 – 104	40	LCF0108 English Rose
	105 – 106	41	LCF0109 Light Salmon
	107 – 109	42	LCF0110 Middle Rose
	110 – 112	43	LCF0111 Dark Pink
	113 – 114	44	LCF0113 Magenta
	115 – 117	45	LCF0127 Smokey Pink
	118 – 119	46	LCF0128 Bright Pink
	120 – 122	47	LCF0148 Bright Rose
	123 – 124	48	LCF0151 Gold Tint
	125 – 127	49	LCF0153 Pale Salmon
	128 – 129	50	LCF0154 Pale Rose
	130 – 132	51	LCF0157 Pink
	133 – 135	52	LCF0164 Flame Red
	136 – 137	53	LCF0176 Loving Amber
	138 – 140	54	LCF0182 Light Red
	141 – 142	55	LCF0192 Flesh Pink
	143 – 145	56	LCF0332 S.Rose Pink
	146 – 147	57	LCS0705 Lily Frost
	148 – 150	58	LCS0749 Hampshire Rose
	151 – 152	59	LCS0750 Durham Frost
	153 – 155	60	L700789 Blood Red
	156 – 255	61 - 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Orange

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 141 ~ 152)	0 - 4	1	RCL0002	Bastard Amber
	5 - 7	2	RCL0008	Pale Gold
	8 - 10	3	RCL0016	Light Amber
	11 - 12	4	RCL0017	Light Flame
	13 - 15	5	RCL0018	Flame
8 (for Gel 2) (Preset CH7: 141 ~ 152)	16 - 17	6	RCL0023	Orange
	18 - 20	7	RCL0099	Chocolate
	21 - 22	8	RCL0302	Pale Bastard Amber
	23 - 25	9	RCL0316	Gallo Gold
	26 - 27	10	RSS2002	VS-Orange
	28 - 30	11	L600604	Full CT
	31 - 33	12	L600651	HI Sodium
	34 - 35	13	L600652	Urban Sodium
	36 - 38	14	L700747	Easy White
	39 - 40	15	L700773	Cardbox Amber
	41 - 43	16	L700776	Nectarine
	44 - 45	17	L700778	Millennium Gold
	46 - 48	18	LCF0004	Med.Bastard Amber
	49 - 50	19	LCF0009	Pale Amber Gold
	51 - 53	20	LCF0017	Surprise Peach
	54 - 55	21	LCF0021	Gold Amber
	56 - 58	22	LCF0022	Dark Amber
	59 - 61	23	LCF0105	Orange
	62 - 63	24	LCF0134	Golden Amber
	64 - 66	25	LCF0135	Deep Golden Amber
	67 - 68	26	LCF0147	Apricot
	69 - 71	27	LCF0152	Pale Gold
	72 - 73	28	LCF0156	Chocolate
	74 - 76	29	LCF0162	Bastard Amber
	77 - 78	30	LCF0179	Chrome Orange
	79 - 81	31	LCS0774	Soft Amber Key 1
	82 - 84	32	LCS0775	Soft Amber Key 2
	85 - 86	33	LCS0791	Moroccan Frost
	87 - 255	34 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Yellow

DMX Channel	Value	Percentage	Gel Name	Gel Number	
4 (for Gel 1) (Preset CH3: 153 ~ 165)	0 - 4	1	RCA4515	Yellow 15	
	5 - 7	2	RCA4530	Yellow 30	
	8 - 10	3	RCA4560	Yellow 60	
	11 - 12	4	RCA4590	Yellow 90	
	13 - 15	5	RCL0006	No Color Straw	
8 (for Gel 2) (Preset CH7: 153 ~ 165)	16 - 17	6	RCL0012	Straw	
	18 - 20	7	RCL0310	Daffodil	
	21 - 22	8	RSS2003	VS-Yellow	
	23 - 25	9	L600650	Industry Sodium	
	26 - 27	10	L600653	LO Sodium	
	28 - 30	11	L700742	Bram Brown	
	31 - 33	12	L700744	Dirty White	
	34 - 35	13	L700746	Brown	
	36 - 38	14	L700763	Wheat	
	39 - 40	15	L700764	Sun Colour Straw	
	41 - 43	16	L700765	L. Yellow	
	44 - 45	17	LCF0010	Med. Yellow	
	46 - 48	18	LCF0013	Straw Tint	
	49 - 50	19	LCF0015	Deep Straw	
	51 - 53	20	LCF0020	Med. Amber	
	54 - 55	21	LCF0100	Spring Yellow	
	56 - 58	22	LCF0101	Yellow	
	59 - 61	23	LCF0102	Light Amber	
	62 - 63	24	LCF0103	Straw	
	64 - 66	25	LCF0104	Deep Amber	
	67 - 68	26	LCF0159	No Color Straw	
	69 - 255	27 - 100			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Green

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 166 ~ 178)	0 - 4	1	RCA4390	Cyan 90
	5 - 7	2	RCA4415	Green 15
	8 - 10	3	RCA4430	Green 30
	11 - 12	4	RCA4460	Green 60
	13 - 15	5	RCA4490	Green 90
8 (for Gel 2) (Preset CH7: 166 ~ 178)	16 - 17	6	RCL0087	Pale Yellow Green
	18 - 20	7	RCL0088	Light Green
	21 - 22	8	RCL0089	Moss Green
	23 - 25	9	RCL0091	Primary Green
	26 - 27	10	RCL0092	Turquoise
	28 - 30	11	RCL0093	Blue Green
	31 - 33	12	RSS2004	VS-Green
	34 - 35	13	RSS2005	VS-Cyan
	36 - 38	14	L700728	Steel Green
	39 - 40	15	L700730	Liberty Green
	41 - 43	16	L700731	Dirty Ice
	44 - 45	17	L700733	Damp Squib
	46 - 48	18	L700738	JAS Green
	49 - 50	19	LCF0088	Lime Green
	51 - 53	20	LCF0089	Moss Green
	54 - 55	21	LCF0090	Dark Yellow Green
	56 - 58	22	LCF0121	L. Green
	59 - 61	23	LCF0122	Fern Green
	62 - 63	24	LCF0124	Dark Green
	64 - 66	25	LCF0131	Marine Blue
	67 - 68	26	LCF0138	Pale Green
	69 - 71	27	LCF0139	Primary Green
	72 - 255	28 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Blue

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 179 ~ 191)	0 - 4	1	RCA4215	Blue 15
	5 - 7	2	RCA4230	Blue 30
	8 - 10	3	RCA4260	Blue 60
	11 - 12	4	RCA4290	Blue 90
	13 - 15	5	RCA4307	Cyan 7
8 (for Gel 2) (Preset CH7: 179 ~ 191)	16 - 17	6	RCA4315	Cyan 15
	18 - 20	7	RCA4330	Cyan 30
	21 - 22	8	RCA4360	Cyan 60
	23 - 25	9	RCL0060	No Color Blue
	26 - 27	10	RCL0062	Booster Blue
	28 - 30	11	RCL0065	Daylight Blue
	31 - 33	12	RCL0077	Green Blue
	34 - 35	13	RCL0080	Primary Blue
	36 - 38	14	RCL0083	Med. Blue
	39 - 40	15	RCL0360	Clearwater
	41 - 43	16	RCL0362	Tipton Blue
	44 - 45	17	RCL0364	Blue Bell
	46 - 48	18	RCL0365	Tharon Delft Blue
	49 - 50	19	RCL0375	Cerulean Blue
	51 - 53	20	RCL0376	Bermuda Blue
	54 - 55	21	RCL0378	Alice Blue
	56 - 58	22	RCL0381	Baldassari Blue
	59 - 61	23	RSS2006	VS-Azure
	62 - 63	24	RSS2007	VS-Blue
	64 - 66	25	RSS2008	VS-Indigo
	67 - 68	26	L600600	Arctic White
	69 - 71	27	L600601	Silver
	72 - 73	28	L600602	Platinum
	74 - 76	29	L600603	Moonlight White
	77 - 78	30	L700708	Cool Lavender
	79 - 81	31	L700710	Spir Sp Blue
	82 - 84	32	L700711	Cold Blue
	85 - 86	33	L700712	Bedford Blue
	87 - 89	34	L700714	Elysian Blue

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
	90 – 91	35	L700715 Cabana Blue
	92 – 94	36	L700716 Mik. Blue
	95 – 96	37	L700719 Colour Wash Blue
	97 – 99	38	L700721 Berry Blue
	100 – 101	39	L700723 Virgin Blue
	102 – 104	40	L700724 Ocean Blue
	105 – 106	41	L700725 Old Steel Blue
	107 – 109	42	LCC0200 CTB Double
	110 – 112	43	LCF0061 Mist Blue
	113 – 114	44	LCF0063 Pale Blue
	115 – 117	45	LCF0068 Sky Blue
	118 – 119	46	LCF0075 Evening Blue
	120 – 122	47	LCF0079 Just Blue
	123 – 124	48	LCF0085 Deeper Blue
	125 – 127	49	LCF0115 Peacock Blue
	128 – 129	50	LCF0117 Steel Blue
	130 – 132	51	LCF0118 Light Blue
	133 – 135	52	LCF0120 Deep Blue
	136 – 137	53	LCF0140 Summer Blue
	138 – 140	54	LCF0141 Bright Blue
	141 – 142	55	LCF0143 Pale Navy Blue
	143 – 145	56	LCF0144 No Color Blue
	146 – 147	57	LCF0161 Slate Blue
	148 – 150	58	LCF0165 Daylight Blue
	151 – 152	59	LCF0174 Dark Steel Blue
	153 – 155	60	LCF0195 Zenith Blue
	156 – 157	61	LCF0196 True Blue
	159 – 160	62	LCF0197 Alice Blue
	161 – 163	63	LCF0198 Palace Blue
	164 – 165	64	LCF0199 Regal Blue
	166 – 168	65	LCS0221 Blue Frost
	169 – 170	66	LCS0224 Daylite Blue Frost
	171 – 173	67	LCS0717 Shanklin Frost
	174 – 175	68	LCS0718 1/2 Shanklin Frost
	176 – 178	69	LCS0720 Dh Daylite Frost
	179 – 255	70 - 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 16 : GEL, 8 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Purple

DMX Channel	Value	Percentage	Gel Name	Gel Number
4 (for Gel 1) (Preset CH3: 192 ~ 203)	0 - 4	1	RSS2010	VS-Magenta
	5 - 7	2	RSS2009	VS-Violet
	8 - 10	3	RCL0051	Surprise Pink
	11 - 12	4	RCL0047	Light Rose Purple
	13 - 15	5	RCL0037	Pale Rose Pink
8 (for Gel 2) (Preset CH7: 192 ~ 203)	16 - 17	6	RCA4990	Lavender 90
	18 - 20	7	RCA4960	Lavender 60
	21 - 22	8	RCA4930	Lavender 30
	23 - 25	9	RCA4915	Lavender 15
	26 - 27	10	RCA4790	Magenta 90
	28 - 30	11	RCA4760	Magenta 60
	31 - 33	12	RCA4730	Magenta 30
	34 - 35	13	RCA4715	Magenta 15
	36 - 38	14	L700700	Perfect Lavender
	39 - 40	15	L700701	Provence
	41 - 43	16	L700702	Sp Pale Lavender
	44 - 45	17	L700703	Cold Lavender
	46 - 48	18	L700704	Lily
	49 - 50	19	L700706	King Fals Lavender
	51 - 53	20	L700709	Electric Lilac
	54 - 55	21	LCF0003	Lavender Tint
	56 - 58	22	LCF0052	Light Lavender
	59 - 61	23	LCF0053	Paler Lavender
	62 - 63	24	LCF0058	Lavender
	64 - 66	25	LCF0136	Pale Lavender
	67 - 68	26	LCF0137	Special Lavender
	69 - 71	27	LCF0142	Pale Violet
	72 - 73	28	LCF0169	Lilac Tint
	74 - 76	29	LCF0170	Deep Lavender
	77 - 78	30	LCF0180	Dark Lavender
	79 - 81	31	LCF0194	Surprise Pink
	82 - 255	32 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142
 Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
1 (hi)	0 - 65535	0 - 100	Master Intensity
3 (hi)	Gel 1, CCT Selection		
4 (lo)	0 - 32767	0 - 50	3.200 K
	32768 - 65535	51 - 100	5.600 K
5 (hi)	Gel 1: Filter Class		
6 (lo)	0 - 3327	0 - 4	CTB under Color Correction
	3328 - 6555	5 - 9	CTO under Color Correction
	6556 - 9983	10 - 14	CTS under Color Correction
	9984 - 13055	15 - 19	+/- Green under Color Correction
	13056 - 15871	20 - 24	Misc under Color Correction
	15872 - 32767	25 - 49	Reserved
	32768 - 36095	50 - 54	Red under Color Filter
	36096 - 39167	55 - 59	Orange under Color Filter
	39168 - 42495	60 - 64	Yellow under Color Filter
	42496 - 45823	65 - 69	Green under Color Filter
	45824 - 49151	70 - 74	Blue under Color Filter
	49152 - 52223	75 - 79	Purple under Color Filter
	52224 - 65535	80 - 100	Reserved
7 (hi)	0 - 65535	0 - 100	Gel 1: Filter Code
8 (lo)			
9 (hi)	0 - 65535	0 - 100	Cross Fade from Gel 1 to Gel2
10 (lo)			

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
11 (hi)	Gel 2, CCT Selection		
12 (lo)	0 - 32767	0 - 50	3.200 K
	32768 - 65535	51 - 100	5.600 K
13 (hi)	Gel 2: Filter Class		
14 (lo)	0 - 3327	0 - 4	CTB under Color Correction
	3328 - 6555	5 - 9	CTO under Color Correction
	6556 - 9983	10 - 14	CTS under Color Correction
	9984 - 13055	15 - 19	+/- Green under Color Correction
	13056 - 15871	20 - 24	Misc under Color Correction
	15872 - 32767	25 - 49	Reserved
	32768 - 36095	50 - 54	Red under Color Filter
	36096 - 39167	55 - 59	Orange under Color Filter
	39168 - 42495	60 - 64	Yellow under Color Filter
	42496 - 45823	65 - 69	Green under Color Filter
	45824 - 49151	70 - 74	Blue under Color Filter
	49152 - 52223	75 - 79	Purple under Color Filter
	52224 - 65535	80 - 100	Reserved
15 (hi)	0 - 65535	0 - 100	Gel 2: Filter Code
16 (lo)			
17	Transition Type		
	0 - 41	0~16	Direct
	42 - 83	17~32	Through White Point
	84 - 125	33~49	Through Black Point
	126 - 167	50~65	Dissolve (future development plan)
	168 - 209	66~82	Over White Point (future development plan)
	210 - 255	83~100	Under White point (future development plan)

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
Aurora V1 400C 0x0201
Aurora V2 220C 0x0211
Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
18	Fan control		
	0 - 9	0 - 3	As Fixture Setting
	10 - 49	4 - 19	Quiet Mode
	50 - 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 - 175	60 - 68	Full Speed
	176 - 200	69 - 78	Full Speed but Limited Output 80%
	201 - 225	79 - 88	Full Speed but Limited Output 60%
	226 - 249	89 - 97	Full Speed but Limited Output 40%
250 - 255	98 - 100	Reserved for future use	
19~21	0 - 255	0 - 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for CTB under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
7,8 (for Gel 1) (Preset CH5,6: 0 – 3275	0 - 1279	1	RCC3220	CTB Double
	1280 - 2047	2	RCC3202	CTB Full
	2048 - 2815	3	RCC3203	CTB 3/4
	2816 - 3327	4	RCC3204	CTB 1/2
	3328 - 4095	5	RCC3208	CTB 1/4
15,16 (for Gel 2) (Preset CH13,14: 0– 3275	4096 - 4607	6	RCC3216	CTB 1/8
	4608 - 5375	7	LCC0283	CTB 1-1/2
	5376 - 5887	8	LCC0201	CTB Full
	5888 - 6655	9	LCC0281	CTB 3/4
	6656 - 7167	10	LCC0202	CTB 1/2
	7168 - 7935	11	LCC0203	CTB 1/4
	7936 - 8703	12	LCC0218	CTB 1/8
	8704 - 65535	13 - 100		Reserved for future use

Filter code for CTO under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
7,8 (for Gel 1) (Preset CH5,6: 3276 – 6553	0 - 1279	1	RCC3407	CTO Full
	1280 - 2047	2	RCC3411	CTO 3/4
	2048 - 2815	3	RCC3408	CTO 1/2
	2816 - 3327	4	RCC3409	CTO 1/4
	3328 - 4095	5	RCC3410	CTO 1/8
15,16 (for Gel 2) (Preset CH13,14: 3276 – 6553	4096 - 4607	6	LCC0286	CTO 1-1/2
	4608 - 5375	7	LCC0208	CTO Full+6ND
	5376 - 5887	8	LCC0207	CTO Full+3ND
	5888 - 6655	9	LCC0206	CTO 1/4
	6656 - 7167	10	LCC0287	CTO Double
	7168 - 7935	11	LCC0204	CTO Full
	7936 - 8703	12	LCC0285	CTO 3/4
	8704 - 9215	13	LCC0205	CTO 1/2
	9216 - 9983	14	LCC0223	CTO 1/8
	9984 - 65535	15 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142
 Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for CTS under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
7,8 (for Gel 1) (Preset CH5,6: 6554 - 9830	0 - 1279	1	RCC3441	CTS Full
	1280 - 2047	2	RCC3442	CTS 1/2
	2048 - 2815	3	RCC3443	CTS 1/4
	2816 - 3327	4	RCC3444	CTS 1/8
	3328 - 4095	5	LCC0441	CTS Full
15,16 (for Gel 2) (Preset CH13,14: 6554 - 9830	4096 - 4607	6	LCC0442	CTS 1/2
	4608 - 5375	7	LCC0443	CTS 1/4
	5376 - 5887	8	LCC0444	CTS 1/8
	5888 - 65535	9 - 100		Reserved for future use

Filter code for +/-Green under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
7,8 (for Gel 1) (Preset CH5,6: 9831 - 13106	0 - 1279	1	RCC3304	Plusgreen Full
	1280 - 2047	2	RCC3315	Plusgreen 1/2
	2048 - 2815	3	RCC3316	Plusgreen 1/4
	2816 - 3327	4	RCC3317	Plusgreen 1/8
	3328 - 4095	5	RCC3308	Minusgreen Full
15,16 (for Gel 2) (Preset CH13,14: 9831 - 13106	4096 - 4607	6	RCC3309	Minusgreen 3/4
	4608 - 5375	7	RCC3313	Minusgreen 1/2
	5376 - 5887	8	RCC3314	Minusgreen 1/4
	5888 - 6655	9	RCC3318	Minusgreen 1/8
	6656 - 7167	10	LCC0244	L.Plus Green
	7168 - 7935	11	LCC0245	Plus Green 1/2
	7936 - 8703	12	LCC0246	Plus Green 1/4
	8704 - 9215	13	LCC0278	Plus Green 1/8
	9216 - 9983	14	LCC0247	L. Minus Green
	9984 - 10495	15	LCC0248	Minus Green 1/2
	10496 - 11263	16	LCC0249	Minus Green 1/4
	11264 - 11775	17	LCC0279	Minus Green 1/8
	11776 - 65535	18 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
Aurora V1 400C 0x0201
Aurora V2 220C 0x0211
Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel Value Percent Function
Filter code for Misc under Color Correction

DMX Channel	Value	Percentage	Gel Name	Gel Number
7,8 (for Gel 1) (Preset CH5,6: 13107 – 16383	0 - 1279	1	RCC3102	Tough MT2
	1280 - 2047	2	RCC3106	Tough MTY
	2048 - 2815	3	RCC3107	Tough Y-1
	2816 - 3327	4	RCC3134	Tough MT
	3328 - 4095	5	RCC3150	Industrial Vapor
15,16 (for Gel 2) (Preset CH13,14: 13107 – 16383	4096 - 4607	6	RCC3152	Urban Vapor
	4608 - 5375	7	RCC3310	Fluoro Ffilter
	5376 - 5887	8	LCC0212	LCT Yellow (Y1)
	5888 - 6655	9	LCC0213	White Flame Green
	6656 - 7167	10	LCC0219	Fluo Green
	7168 - 7935	11	LCC0230	S.Corr LCT Yellow
	7936 - 8703	12	LCC0232	S Corr WF Green
	8704 - 9215	13	LCC0236	HMI (to Tungsten)
	9216 - 9983	14	LCC0237	CID (to Tungsten)
	9984 - 10495	15	LCC0238	CSI (to Tungsten)
	10496 - 11263	16	LCC0241	L.Flou 5700K
	11264 - 11775	17	LCC0242	L.Flou 4300K
	11776 - 12543	18	LCC0243	L.Flou 3600K
12544 - 65535	19 - 100		Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142
 Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
Filter code for Red			
DMX Channel	Value	Percentage	Gel Name Gel Number
7,8 (for Gel 1) (Preset CH5,6: 32768 – 36044	0 - 1279	1	RCA4615 Red 15
	1280 - 2047	2	RCA4630 Red 30
	2048 - 2815	3	RCA4660 Red 60
	2816 - 3327	4	RCA4690 Red 90
	3328 - 4095	5	RCA4815 Pink 15
15,16 (for Gel 2) (Preset CH13,14: 32768 – 36044	4096 - 4607	6	RCA4830 Pink 30
	4608 - 5375	7	RCA4860 Pink 60
	5376 - 5887	8	RCA4890 Pink 90
	5888 - 6655	9	RCC3102 Tough MT2
	6656 - 7167	10	RCL0021 Golden Amber
	7168 - 7935	11	RCL0026 Light Red
	7936 - 8703	12	RCL0033 No Color Pink
	8704 - 9215	13	RCL0034 Flesh Pink
	9216 - 9983	14	RCL0041 Salmon
	9984 - 10495	15	RCL0042 Deep Salmon
	10496 - 11263	16	RCL0044 Middle Rose
	11264 - 11775	17	RCL0318 Mayan Sun
	11776 - 12543	18	RCL0321 Soft Golden Amber
	12544 - 13055	19	RCL0325 Henna Sky
	13056 - 13823	20	RCL0333 Blush Pink
	13824 - 14335	21	RSS2001 VS-Red
	14336 - 15103	22	L700748 Seedy Pink
	15104 - 15871	23	L700779 Bastard Pink
	15872 - 16383	24	L700781 Terry Red
	16384 - 17151	25	L700790 Moroccan Pink
17152 - 17663	26	L700794 Pretty n Pink	
17664 - 18431	27	L700795 Magical Magenta	
18432 - 18943	28	LCF0002 Rose Pink	
18944 - 19711	29	LCF0008 Dark Salmon	
19712 - 20223	30	LCF0019 Fire	
20224 - 20991	31	LCF0024 Scarlet	
20992 - 21759	32	LCF0025 Sunset Red	
21760 - 22271	33	LCF0026 Bright Red	
22272 - 23039	34	LCF0035 Light Pink	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
Aurora V1 400C 0x0201
Aurora V2 220C 0x0211
Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
	23040 - 23551	35	LCF0036 Med. Pink
	23552 - 24319	36	LCF0046 Dark Magenta
	24320 - 24831	37	LCF0048 Rose Purple
	24832 - 25599	38	LCF0106 Primary Red
	25600 - 26111	39	LCF0107 Light Rose
	26112 - 26879	40	LCF0108 English Rose
	26880 - 27391	41	LCF0109 Light Salmon
	27392 - 28159	42	LCF0110 Middle Rose
	28160 - 28927	43	LCF0111 Dark Pink
	28928 - 29439	44	LCF0113 Magenta
	29440 - 30207	45	LCF0127 Smokey Pink
	30208 - 30719	46	LCF0128 Bright Pink
	30720 - 31487	47	LCF0148 Bright Rose
	31488 - 31999	48	LCF0151 Gold Tint
	32000 - 32767	49	LCF0153 Pale Salmon
	32768 - 33279	50	LCF0154 Pale Rose
	33280 - 34047	51	LCF0157 Pink
	34048 - 34815	52	LCF0164 Flame Red
	34816 - 35327	53	LCF0176 Loving Amber
	35328 - 36095	54	LCF0182 Light Red
	36096 - 36607	55	LCF0192 Flesh Pink
	36608 - 37375	56	LCF0332 S.Rose Pink
	37376 - 37887	57	LCS0705 Lily Frost
	37888 - 38655	58	LCS0749 Hampshire Rose
	38656 - 39167	59	LCS0750 Durham Frost
	39168 - 39935	60	L700789 Blood Red
	39936 - 65535	61 - 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142
 Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
Filter code for Orange			
DMX Channel	Value	Percentage	Gel Name Gel Number
7,8 (for Gel 1) (Preset CH5,6: 36045 – 39320	0 - 1279	1	RCL0002 Bastard Amber
	1280 - 2047	2	RCL0008 Pale Gold
	2048 - 2815	3	RCL0016 Light Amber
	2816 - 3327	4	RCL0017 Light Flame
	3328 - 4095	5	RCL0018 Flame
15,16 (for Gel 2) (Preset CH13,14: 36045 – 39320	4096 - 4607	6	RCL0023 Orange
	4608 - 5375	7	RCL0099 Chocolate
	5376 - 5887	8	RCL0302 Pale Bastard Amber
	5888 - 6655	9	RCL0316 Gallo Gold
	6656 - 7167	10	RSS2002 VS-Orange
	7168 - 7935	11	L600604 Full CT
	7936 - 8703	12	L600651 HI Sodium
	8704 - 9215	13	L600652 Urban Sodium
	9216 - 9983	14	L700747 Easy White
	9984 - 10495	15	L700773 Cardbox Amber
	10496 - 11263	16	L700776 Nectarine
	11264 - 11775	17	L700778 Millennium Gold
	11776 - 12543	18	LCF0004 Med.Bastard Amber
	12544 - 13055	19	LCF0009 Pale Amber Gold
	13056 - 13823	20	LCF0017 Surprise Peach
	13824 - 14335	21	LCF0021 Gold Amber
	14336 - 15103	22	LCF0022 Dark Amber
	15104 - 15871	23	LCF0105 Orange
	15872 - 16383	24	LCF0134 Golden Amber
	16384 - 17151	25	LCF0135 Deep Golden Amber
17152 - 17663	26	LCF0147 Apricot	
17664 - 18431	27	LCF0152 Pale Gold	
18432 - 18943	28	LCF0156 Chocolate	
18944 - 19711	29	LCF0162 Bastard Amber	
19712 - 20223	30	LCF0179 Chrome Orange	
20224 - 20991	31	LCS0774 Soft Amber Key 1	
20992 - 21759	32	LCS0775 Soft Amber Key 2	
21760 - 22271	33	LCS0791 Moroccan Frost	
22272 - 65535	34 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Yellow

DMX Channel	Value	Percentage	Gel Name	Gel Number
7,8 (for Gel 1) (Preset CH5,6: 39321 – 42597	0 - 1279	1	RCA4515	Yellow 15
	1280 - 2047	2	RCA4530	Yellow 30
	2048 - 2815	3	RCA4560	Yellow 60
	2816 - 3327	4	RCA4590	Yellow 90
	3328 - 4095	5	RCL0006	No Color Straw
15,16 (for Gel 2) (Preset CH13,14: 39321 – 42597	4096 - 4607	6	RCL0012	Straw
	4608 - 5375	7	RCL0310	Daffodil
	5376 - 5887	8	RSS2003	VS-Yellow
	5888 - 6655	9	L600650	Industry Sodium
	6656 - 7167	10	L600653	LO Sodium
	7168 - 7935	11	L700742	Bram Brown
	7936 - 8703	12	L700744	Dirty White
	8704 - 9215	13	L700746	Brown
	9216 - 9983	14	L700763	Wheat
	9984 - 10495	15	L700764	Sun Colour Straw
	10496 - 11263	16	L700765	L. Yellow
	11264 - 11775	17	LCF0010	Med. Yellow
	11776 - 12543	18	LCF0013	Straw Tint
	12544 - 13055	19	LCF0015	Deep Straw
	13056 - 13823	20	LCF0020	Med. Amber
	13824 - 14335	21	LCF0100	Spring Yellow
	14336 - 15103	22	LCF0101	Yellow
	15104 - 15871	23	LCF0102	Light Amber
	15872 - 16383	24	LCF0103	Straw
	16384 - 17151	25	LCF0104	Deep Amber
	17152 - 17663	26	LCF0159	No Color Straw
17664 - 65535	27 - 100		Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel Value Percent Function
 Filter code for Green

DMX Channel	Value	Percentage	Gel Name	Gel Number
7,8 (for Gel 1) (Preset CH5,6: 42598 – 45874	0 - 1279	1	RCA4390	Cyan 90
	1280 - 2047	2	RCA4415	Green 15
	2048 - 2815	3	RCA4430	Green 30
	2816 - 3327	4	RCA4460	Green 60
	3328 - 4095	5	RCA4490	Green 90
15,16 (for Gel 2) (Preset CH13,14: 42598 – 45874	4096 - 4607	6	RCL0087	Pale Yellow Green
	4608 - 5375	7	RCL0088	Light Green
	5376 - 5887	8	RCL0089	Moss Green
	5888 - 6655	9	RCL0091	Primary Green
	6656 - 7167	10	RCL0092	Turquoise
	7168 - 7935	11	RCL0093	Blue Green
	7936 - 8703	12	RSS2004	VS-Green
	8704 - 9215	13	RSS2005	VS-Cyan
	9216 - 9983	14	L700728	Steel Green
	9984 - 10495	15	L700730	Liberty Green
	10496 - 11263	16	L700731	Dirty Ice
	11264 - 11775	17	L700733	Damp Squib
	11776 - 12543	18	L700738	JAS Green
	12544 - 13055	19	LCF0088	Lime Green
	13056 - 13823	20	LCF0089	Moss Green
	13824 - 14335	21	LCF0090	Dark Yellow Green
	14336 - 15103	22	LCF0121	L. Green
	15104 - 15871	23	LCF0122	Fern Green
	15872 - 16383	24	LCF0124	Dark Green
	16384 - 17151	25	LCF0131	Marine Blue
17152 - 17663	26	LCF0138	Pale Green	
17664 - 18431	27	LCF0139	Primary Green	
18432 - 65535	28 - 100		Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
Filter code for Blue			
DMX Channel	Value	Percentage	Gel Name Gel Number
7,8 (for Gel 1) (Preset CH5,6: 45875 – 49151	0 - 1279	1	RCA4215 Blue 15
	1280 - 2047	2	RCA4230 Blue 30
	2048 - 2815	3	RCA4260 Blue 60
	2816 - 3327	4	RCA4290 Blue 90
	3328 - 4095	5	RCA4307 Cyan 7
15,16 (for Gel 2) (Preset CH13,14: 45875 – 49151	4096 - 4607	6	RCA4315 Cyan 15
	4608 - 5375	7	RCA4330 Cyan 30
	5376 - 5887	8	RCA4360 Cyan 60
	5888 - 6655	9	RCL0060 No Color Blue
	6656 - 7167	10	RCL0062 Booster Blue
	7168 - 7935	11	RCL0065 Daylight Blue
	7936 - 8703	12	RCL0077 Green Blue
	8704 - 9215	13	RCL0080 Primary Blue
	9216 - 9983	14	RCL0083 Med. Blue
	9984 - 10495	15	RCL0360 Clearwater
	10496 - 11263	16	RCL0362 Tipton Blue
	11264 - 11775	17	RCL0364 Blue Bell
	11776 - 12543	18	RCL0365 Tharon Delft Blue
	12544 - 13055	19	RCL0375 Cerulean Blue
	13056 - 13823	20	RCL0376 Bermuda Blue
	13824 - 14335	21	RCL0378 Alice Blue
	14336 - 15103	22	RCL0381 Baldassari Blue
	15104 - 15871	23	RSS2006 VS-Azure
	15872 - 16383	24	RSS2007 VS-Blue
	16384 - 17151	25	RSS2008 VS-Indigo
17152 - 17663	26	L600600 Arctic White	
17664 - 18431	27	L600601 Silver	
18432 - 18943	28	L600602 Platinum	
18944 - 19711	29	L600603 Moonlight White	
19712 - 20223	30	L700708 Cool Lavender	
20224 - 20991	31	L700710 Spir Sp Blue	
20992 - 21759	32	L700711 Cold Blue	
21760 - 22271	33	L700712 Bedford Blue	
22272 - 23039	34	L700714 Elysian Blue	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
	23040 - 23551	35	L700715 Cabana Blue
	23552 - 24319	36	L700716 Mik. Blue
	24320 - 24831	37	L700719 Colour Wash Blue
	24832 - 25599	38	L700721 Berry Blue
	25600 - 26111	39	L700723 Virgin Blue
	26112 - 26879	40	L700724 Ocean Blue
	26880 - 27391	41	L700725 Old Steel Blue
	27392 - 28159	42	LCC0200 CTB Double
	28160 - 28927	43	LCF0061 Mist Blue
	28928 - 29439	44	LCF0063 Pale Blue
	29440 - 30207	45	LCF0068 Sky Blue
	30208 - 30719	46	LCF0075 Evening Blue
	30720 - 31487	47	LCF0079 Just Blue
	31488 - 31999	48	LCF0085 Deeper Blue
	32000 - 32767	49	LCF0115 Peacock Blue
	32768 - 33279	50	LCF0117 Steel Blue
	33280 - 34047	51	LCF0118 Light Blue
	34048 - 34815	52	LCF0120 Deep Blue
	34816 - 35327	53	LCF0140 Summer Blue
	35328 - 36095	54	LCF0141 Bright Blue
	36096 - 36607	55	LCF0143 Pale Navy Blue
	36608 - 37375	56	LCF0144 No Color Blue
	37376 - 37887	57	LCF0161 Slate Blue
	37888 - 38655	58	LCF0165 Daylight Blue
	38656 - 39167	59	LCF0174 Dark Steel Blue
	39168 - 39935	60	LCF0195 Zenith Blue
	39936 - 40703	61	LCF0196 True Blue
	40704 - 41215	62	LCF0197 Alice Blue
	41216 - 41983	63	LCF0198 Palace Blue
	41984 - 42795	64	LCF0199 Regal Blue
	42496 - 43263	65	LCS0221 Blue Frost
	43264 - 43775	66	LCS0224 Daylite Blue Frost
	43776 - 44543	67	LCS0717 Shanklin Frost
	44544 - 45055	68	LCS0718 1/2 Shanklin Frost
	45056 - 45823	69	LCS0720 Dh Daylite Frost
	45824 - 65535	70 - 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142
 Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 17 : GEL, 16 bit resolution per function, base channels

DMX Channel	Value	Percent	Function
Filter code for Purple			
DMX Channel	Value	Percentage	Gel Name Gel Number
7,8 (for Gel 1) (Preset CH5,6: 49152 – 52427	0 - 1279	1	RSS2010 VS-Magenta
	1280 - 2047	2	RSS2009 VS-Violet
	2048 - 2815	3	RCL0051 Surprise Pink
	2816 - 3327	4	RCL0047 Light Rose Purple
	3328 - 4095	5	RCL0037 Pale Rose Pink
15,16 (for Gel 2) (Preset CH13,14: 49152 – 52427	4096 - 4607	6	RCA4990 Lavender 90
	4608 - 5375	7	RCA4960 Lavender 60
	5376 - 5887	8	RCA4930 Lavender 30
	5888 - 6655	9	RCA4915 Lavender 15
	6656 - 7167	10	RCA4790 Magenta 90
	7168 - 7935	11	RCA4760 Magenta 60
	7936 - 8703	12	RCA4730 Magenta 30
	8704 - 9215	13	RCA4715 Magenta 15
	9216 - 9983	14	L700700 Perfect Lavender
	9984 - 10495	15	L700701 Provence
	10496 - 11263	16	L700702 Sp Pale Lavender
	11264 - 11775	17	L700703 Cold Lavender
	11776 - 12543	18	L700704 Lily
	12544 - 13055	19	L700706 King Fals Lavender
	13056 - 13823	20	L700709 Electric Lilac
	13824 - 14335	21	LCF0003 Lavender Tint
	14336 - 15103	22	LCF0052 Light Lavender
	15104 - 15871	23	LCF0053 Paler Lavender
	15872 - 16383	24	LCF0058 Lavender
	16384 - 17151	25	LCF0136 Pale Lavender
	17152 - 17663	26	LCF0137 Special Lavender
	17664 - 18431	27	LCF0142 Pale Violet
	18432 - 18943	28	LCF0169 Lilac Tint
	18944 - 19711	29	LCF0170 Deep Lavender
	19712 - 20223	30	LCF0180 Dark Lavender
20224 - 20991	31	LCF0194 Surprise Pink	
20992 - 65535	32 - 100		Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 18 : x,y Coordinates, 8 bit resolution per function

DMX Channel	Value	Percent	Function
1	Master Intensity		
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	X1 Coordinate (0.0 – 0.8)
3	0 – 255	0 – 100	Y1 Coordinate (0.0 – 0,8)
4	0 – 255	0 – 100	Cross Fade X1, Y1 → X2, Y2
5	0 – 255	0 – 100	X2 Coordinate (0.0 – 0.8)
6	0 – 255	0 – 100	Y2 Coordinate (0.0 – 0,8)
7	Transition Type		
	0~41	0~16	Direct
	42~83	17~32	Through White Point
	84~125	33~49	Through Black Point
	126~167	50~65	Dissolve (future development plan)
	168~209	66~82	Over White Point (future development plan)
	210~255	83~100	Under White point (future development plan)
8	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
9 ~ 11			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 19 : x,y Coordinates 16 bit resolution per function

DMX Channel	Value	Percent	Function
1 (Hi)			Master Intensity
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (hi)	0 –65535	0 – 100	X1 Coordinate (0.0 – 0.8)
4 (lo)			
5 (hi)	0 –65535	0 – 100	Y1 Coordinate (0.0 – 0,8)
6 (lo)			
7	0 – 255	0 – 100	Cross Fade X1, Y1 → X2, Y2
8 (hi)	0 –65535	0 – 100	X2 Coordinate (0.0 – 0.8)
9 (lo)			
10 (hi)	0 –65535	0 – 100	Y2 Coordinate (0.0 – 0,8)
11 (lo)			
12	Transition Type		
	0~41	0~16	Direct
	42~83	17~32	Through White Point
	84~125	33~49	Through Black Point
	126~167	50~65	Dissolve (future development plan)
	168~209	66~82	Over White Point (future development plan)
	210~255	83~100	Under White point (future development plan)
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	
14~16			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 20 : Effects, 8 bit resolution per function

DMX Channel	Value	Percent	Function
1	Master Intensity		
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	Effect Selection		
	0 – 9	0 – 4	No Effect
	10 – 19	5 – 7	Party
	20 – 29	8 – 11	Candle
	30 – 39	12 – 15	Clouds Passing
	40 – 49	16 – 19	Club
	50 – 59	20 – 23	Color Chase
	60 – 69	24 – 27	Explosion
	70 – 79	28 – 31	Fire
	80 – 89	32 – 35	Fireworks
	90 – 99	36 – 39	Flu.Flicker
	100 – 109	40 – 43	Lightning
	110 – 119	44 – 47	Paparazzi
	120 – 129	48 – 51	Police Car
	130 – 139	52 – 55	Process
	140 – 149	56 – 58	Pulsing
	150 – 159	59 – 62	Strobe
160 – 169	63 – 66	TV	
170 – 179	67 – 70	Welding	
180 - 189	71 - 74	N/A	
180 - 255	75 - 100	No Effect (Reserved for future use)	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 20 : Effects, 8 bit resolution per function

DMX Channel	Value	Percent	Function
3	0 – 255	0 – 100	Effect Parameter 1 (Like PARTY, SPEED)
4	0 – 255	0 – 100	Effect Parameter 2 (Like PARTY , SATURATION)
5	0 – 255	0 – 100	Effect Parameter 3
6	0 – 255	0 – 100	Effect Parameter 4
7	0 – 255	0 – 100	Effect Parameter 5
8	0 – 255	0 – 100	Effect Parameter 6
9	0 – 255	0 – 100	Effect Parameter 7
10	0 – 255	0 – 100	Effect Parameter 8
11	0 – 255	0 – 100	Effect Parameter 9
12	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	AutoMode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use
13~15			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Party Effect Preset: Ch2: 10-19				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	0 – 255	0 – 100	Saturation

Candle Preset: Ch2: 20-29				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	Color Temperature		
		0 – 84	0 – 33	1400 ~ 1700K
		85 – 170	34 – 66	1700 ~ 2000K
		171 – 255	67 – 100	2000 ~ 2300K

Cloud Passing Preset: Ch2: 30-39				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	0 – 255	0 – 100	Offset <i>*Number 0 - 50 (Every 5 DMX values is a new</i>
3	5	255	100	Sync (Jump to "Offset" section)

Club Preset: Ch2: 40-49				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	Type		
		0 - 31	0 - 12	3 Colors
		32 - 63	13 - 24	6 Colors
		64 - 95	25 - 37	9 Colors
		96 - 127	38 - 49	12 Colors
		128 - 159	50 - 62	15 Colors
		160 - 191	63 - 74	18 Colors
		192 - 223	75 - 87	21 Colors
224 - 255	88 - 100	24 Colors		

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Color Chase				
Preset: Ch2: 50-59				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	0 – 255	0 – 100	Offset *Number 0 - 50 (Every 5 DMX values is a new
3	5	255	100	Sync (Jump to "Offset" section)

	DMX Channel	Value 8 bit	Percent	Function
Explosion				
Preset: Ch2: 60-69				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 - 127	0 - 49	Auto Explosion Speed (Slow ->Fast)
		128 - 249	50 - 97	Idle (Manual Operation wait for signal)
		250- 255	98 – 100	Manual Trigger
2	4	0 – 255	0 – 100	Decay
3	5	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
245~255	97~100	full plus green		
5	7	0 - 255	0 - 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)

	DMX Channel	Value 8 bit	Percent	Function
Fire				
Preset: Ch2: 70-79				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	Color Temperature		
		0 – 84	0 – 33	Warm
		85 – 170	34 – 66	Neutral
		171 – 255	67 – 100	Cold

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Fireworks				
Preset: Ch2: 80-89				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	Combination		
		0 – 84	0 – 33	RGB
		85 – 170	34 – 66	White
		171 – 255	67 – 100	RGB+White
Flu. Flicker				
Preset: Ch2: 90-99				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	0 – 255	0 – 100	Frequency
3	5	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
245~255	97~100	full plus green		
5	7	0 – 255	0 – 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)
8	10	255	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Lightning				
Preset: Ch2: 100-109				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Frequency
2	4	0 – 255	0 – 100	Density
3	5	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
		245~255	97~100	full plus green
5	7	0 – 255	0 – 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)
8	10	255	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Paparazzi				
Preset: Ch2: 110-119				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Frequency
2	4	Flash Type		
		0 – 127	0 – 50	Flash Bulb
		128 – 255	51 – 100	Modern Flash
3	5	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
245~255	97~100	full plus green		
5	7	0 – 255	0 – 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)
8	10	255	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Police Car				
Preset: Ch2: 120-129				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	Color Combinations		
		0 - 25	0 - 9	Blue
		26 - 50	10 - 19	Red
		51 - 76	20 - 29	Blue and Red
		77 - 101	30 - 39	Blue and White
		102 - 127	40 - 49	Amber
		128 - 152	50 - 59	Blue and Amber
		153 - 178	60 - 69	Red and Amber
		179 - 255	70 - 100	Reserved
2	4	Mode		
		0 - 25	0 - 9	Single Flash
		26 - 50	10 - 19	Double Flash
		51 - 76	20 - 29	Quint Flash
		77 - 101	30 - 39	Quad Flash
		102 - 255	40 - 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Process				
Preset: Ch2: 130-139				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	Direction		
		0 – 127	0 – 50	From Right to Left
		128 – 255	51 – 100	From Left to Right
3	5	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
245~255	97~100	full plus green		
5	7	0 – 255	0 – 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)
8	10	255	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
Pulsing				
Preset: Ch2: 140-149				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Frequency
2	4	0 – 255	0 – 100	Span (Pulse Duration)
3	5	0 – 255	0 – 100	Color temperature CCT
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
245~255	97~100	full plus green		
5	7	0 – 255	0 – 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)
8	10	255	100	Sync

Strobe				
Preset: Ch2: 150-159				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Strobe ON
2	4	0 – 255	0 – 100	Strobe OFF
3	5	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
245~255	97~100	full plus green		
5	7	0 – 255	0 – 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)
8	10	255	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 20 : Effects, 8 bit resolution per function

	DMX Channel	Value	Percent	Function
TV				
Preset: Ch2: 160-169				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	Color Temperature		
		0 – 84	0 – 33	Warm
		85 – 170	34 – 66	Neutral
		171 – 255	67 – 100	Cold
Welding				
Preset: Ch2: 170-179				
Para.	DMX Channel	Value 8 bit	Percent	Function
1	3	0 – 255	0 – 100	Speed
2	4	0 – 255	0 – 100	Min Intensity Level
3	5	0 – 255	0 – 100	Color Temp. (2700K~10000K)
4	6	Green / Magenta Adjustment		
		0~10	0~4	neutral / no effect
		11~20	5~8	full minus green
		21~119	9~46	-99% --> -1%
		120~145	47~57	neutral / no effect
		146~244	58~96	1% --> 99%
245~255	97~100	full plus green		
5	7	0 – 255	0 – 100	Color Change Coefficient White --> Color
6	8	0 – 255	0 – 100	Adjust HUE (0~359)
7	9	0 – 255	0 – 100	Adjust Saturation (0~100%)

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
	1 (Hi)			Master Intensity
	2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
	3	Effect Selection		
		0 – 9	0 – 4	No Effect
		10 – 19	5 – 7	Party
		20 – 29	8 – 11	Candle
		30 – 39	12 – 15	Clouds Passing
		40 – 49	16 – 19	Club
		50 – 59	20 – 23	Color Chase
		60 – 69	24 – 27	Explosion
		70 – 79	28 – 31	Fire
		80 – 89	32 – 35	Fireworks
		90 – 99	36 – 39	Flu.Flicker
		100 – 109	40 – 43	Lightning
		110 – 119	44 – 47	Paparazzi
		120 – 129	48 – 51	Police Car
		130 – 139	52 – 55	Process
		140 – 149	56 – 58	Pulsing
		150 – 159	59 – 62	Strobe
	160 – 169	63 – 66	TV	
	170 – 179	67 – 70	Welding	
	180 – 189	71 – 74	N/A	
	190 - 255	75 - 100	Reserved for future use (No Effect)	
	4			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
	5 (Hi)	Effect Parameter #1		
	6 (Lo)	0 – 65535	0 – 100	Para#1 (Like PARTY, SPEED)
	7 (Hi)	Effect Parameter #2		
	8 (Lo)	0 – 65535	0 – 100	Para #2 (Like PARTY , SATURATION)
	9 (Hi)	Effect Parameter #3		
	10 (Lo)	0 – 65535	0 – 100	Para #3
	11 (Hi)	Effect Parameter #4		
	12 (Lo)	0 – 65535	0 – 100	Para #4
	13 (Hi)	Effect Parameter #5		
	14 (Lo)	0 – 65535	0 – 100	Para #5
	15 (Hi)	Effect Parameter #6		
	16 (Lo)	0 – 65535	0 – 100	Para #6
	17 (Hi)	Effect Parameter #7		
	18 (Lo)	0 – 65535	0 – 100	Para #7
	19 (Hi)	Effect Parameter #8		
	20 (Lo)	0 – 65535	0 – 100	Para #6
	21 (Hi)	Effect Parameter #9		
	22 (Lo)	0 – 65535	0 – 100	Para #7

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
	23			Fan control
		0 – 9	0 – 3	As Fixture Setting
		10 – 49	4 - 19	Quiet Mode
		50 – 99	20 - 39	AutoMode
		100 - 150	40 - 59	Variable
		151 – 175	60 – 68	Full Speed
		176 - 200	69 – 78	Full Speed but Limited Output 80%
		201 - 225	79 – 88	Full Speed but Limited Output 60%
		226 - 249	89 – 97	Full Speed but Limited Output 40%
		250 – 255	98 – 100	Reserved for future use
	24~26			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Party Effect Preset: Ch3: 10-19				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Saturation

Candle Preset: Ch3: 20-29				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi) 8 (Lo)	Color Temperature		
		0 – 21804	0 – 33	1400 ~ 1700K
		21805 – 43520	34 – 66	1700 ~ 2000K
		43521 – 65535	67 – 100	2000 ~ 2300K

Cloud Passing Preset: Ch3: 30-39				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Offset *Number 0 - 50 (Every 500 DMX values is a new Offset)
3	9 (Hi) 10 (Lo)	65535	100	Sync (Jump to "Offset" section)

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Club				
Preset: Ch3: 40-49				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi)	Type		
	8 (Lo)	0 - 8191	0 - 12	3 Colors
		8192 - 16383	13 - 24	6 Colors
		16384 - 24575	25 - 37	9 Colors
		24576 - 32767	38 - 49	12 Colors
		32768 - 40959	50 - 62	15 Colors
		40960 - 49151	63 - 74	18 Colors
		49152 - 57343	75 - 87	21 Colors
	57344 - 65535	88 - 100	24 Colors	

Color Chase				
Preset: Ch3: 50-59				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Offset *Number 0 - 50 (Every 500 DMX values is a new Offset)
3	9 (Hi) 10 (Lo)	65535	100	Sync (Jump to "Offset" section)

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Explosion				
Preset: Ch3: 60-69				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi)	0 - 32767	0 - 49	Auto Explosion Speed (Slow ->Fast)
	6 (Lo)	32768 - 64224	50 - 97	Idle (Manual Operation wait for signal)
		64225- 65535	98 - 100	Manual Trigger
2	7 (Hi)	0 - 65535	0 - 100	Decay
	8 (Lo)			
3	9 (Hi)	0 - 65535	0 - 100	Color Temp. (2700K~10000K)
	10 (Lo)			
4	11 (Hi)	Green / Magenta Adjustment		
	12 (Lo)	0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
60000~65535	93~100	full plus green		
5	13 (Hi)	0 - 65535	0 - 100	Color Change Coefficient White --> Color
	14 (Lo)			
6	15 (Hi)	0 - 65535	0 - 100	Adjust HUE (0~359)
	16 (Lo)			
7	17 (Hi)	0 - 65535	0 - 100	Adjust Saturation (0~100%)
	18 (Lo)			

Fire				
Preset: Ch3: 70-79				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi)	0 - 65535	0 - 100	Speed
	6 (Lo)			
2	7 (Hi)	Color Temperature		
	8 (Lo)	0 - 21804	0 - 33	Warm
		21805 - 43520	34 - 66	Neutral
		43521 - 65535	67 - 100	Cold

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Fireworks				
Preset: Ch3: 80-89				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi)	Combination		
	8 (Lo)	0 – 21804	0 – 33	RGB
		21805 – 43520	34 – 66	White
		43521 – 65535	67 – 100	RGB+White

Flu. Flicker				
Preset: Ch3: 90-99				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Frequency
3	9 (Hi) 10 (Lo)	0 – 65535	0 – 100	Color Temp. (2700K~10000K)
4	11 (Hi)	Green / Magenta Adjustment		
	12 (Lo)	0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
60000~65535	93~100	full plus green		
5	13 (Hi) 14 (Lo)	0 – 65535	0 – 100	Color Change Coefficient White --> Color
6	15 (Hi) 16 (Lo)	0 – 65535	0 – 100	Adjust HUE (0~359)
7	17 (Hi) 18 (Lo)	0 – 65535	0 – 100	Adjust Saturation (0~100%)
8	19 (Hi) 20 (Lo)	65535	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Lightning				
Preset: Ch3: 100-109				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Frequency
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Density
3	9 (Hi) 10 (Lo)	0 – 65535	0 – 100	Color Temp. (2700K~10000K)
4	11 (Hi) 12 (Lo)	Green / Magenta Adjustment		
		0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
		60000~65535	93~100	full plus green
5	13 (Hi) 14 (Lo)	0 – 65535	0 – 100	Color Change Coefficient White --> Color
6	15 (Hi) 16 (Lo)	0 – 65535	0 – 100	Adjust HUE (0~359)
7	17 (Hi) 18 (Lo)	0 – 65535	0 – 100	Adjust Saturation (0~100%)
8	19 (Hi) 20 (Lo)	65535	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Paparazzi				
Preset: Ch3: 110-119				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Frequency
2	7 (Hi)	Flash Type		
	8 (Lo)	0 - 32767	0 – 50	Flash Bulb
		32768 - 65535	51 – 100	Modern Flash
3	9 (Hi) 10 (Lo)	0 – 65535	0 – 100	Color Temp. (2700K~10000K)
4	11 (Hi)	Green / Magenta Adjustment		
	12 (Lo)	0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
60000~65535	93~100	full plus green		
5	13 (Hi) 14 (Lo)	0 – 65535	0 – 100	Color Change Coefficient White --> Color
6	15 (Hi) 16 (Lo)	0 – 65535	0 – 100	Adjust HUE (0~359)
7	17 (Hi) 18 (Lo)	0 – 65535	0 – 100	Adjust Saturation (0~100%)
8	19 (Hi) 20 (Lo)	65535	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Police Car				
Preset: Ch3: 120-129				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	Color Combinations		
		0 - 6553	0 - 9	Blue
		6554 - 13106	10 - 19	Red
		13107 - 19660	20 - 29	Blue and Red
		19661 - 26214	30 - 39	Blue and White
		26215 - 32767	40 - 49	Amber
		32768 - 39221	50 - 59	Blue and Amber
		39222 - 45874	60 - 69	Red and Amber
45875 - 65535	70 - 100	Reserved		
2	7 (Hi) 8 (Lo)	Mode		
		0 - 6553	0 - 9	Single Flash
		6554 - 13106	10 - 19	Double Flash
		13107 - 19660	20 - 29	Quint Flash
		19661 - 26214	30 - 39	Quad Flash
26215 - 65535	40 - 100	Reserved for future use		

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Process				
Preset: Ch3: 130-139				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi)	Direction		
	8 (Lo)	0 - 32767	0 – 50	From Right to Left
		32768 - 65535	51 – 100	From Left to Right
3	9 (Hi) 10 (Lo)	0 – 65535	0 – 100	Color Temp. (2700K~10000K)
4	11 (Hi)	Green / Magenta Adjustment		
	12 (Lo)	0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
60000~65535	93~100	full plus green		
5	13 (Hi) 14 (Lo)	0 – 65535	0 – 100	Color Change Coefficient White --> Color
6	15 (Hi) 16 (Lo)	0 – 65535	0 – 100	Adjust HUE (0~359)
7	17 (Hi) 18 (Lo)	0 – 65535	0 – 100	Adjust Saturation (0~100%)
8	19 (Hi) 20 (Lo)	65535	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Pulsing				
Preset: Ch3: 140-149				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Frequency
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Span (Pulse Duration)
3	9 (Hi) 10 (Lo)	0 – 65535	0 – 100	Color Temp. (2700K~10000K)
4	11 (Hi) 12 (Lo)	Green / Magenta Adjustment		
		0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
		60000~65535	93~100	full plus green
5	13 (Hi) 14 (Lo)	0 – 65535	0 – 100	Color Change Coefficient White --> Color
6	15 (Hi) 16 (Lo)	0 – 65535	0 – 100	Adjust HUE (0~359)
7	17 (Hi) 18 (Lo)	0 – 65535	0 – 100	Adjust Saturation (0~100%)
8	19 (Hi) 20 (Lo)	65535	100	Sync

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Strobe				
Preset: Ch3: 150-159				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Strobe ON
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Strobe OFF
3	9 (Hi) 10 (Lo)	0 – 65535	0 – 100	Color Temp. (2700K~10000K)
4	11 (Hi) 12 (Lo)	Green / Magenta Adjustment		
		0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
5	13 (Hi) 14 (Lo)	0 – 65535	0 – 100	Color Change Coefficient White --> Color
		65535	100	Sync
6	15 (Hi) 16 (Lo)	0 – 65535	0 – 100	Adjust HUE (0~359)
7	17 (Hi) 18 (Lo)	0 – 65535	0 – 100	Adjust Saturation (0~100%)
8	19 (Hi) 20 (Lo)	65535	100	Sync

Para.	DMX Channel	Value 16 bit	Percent	Function
TV				
Preset: Ch3: 160-169				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi) 8 (Lo)	Color Temperature		
		0 – 21804	0 – 33	Warm
		21805 – 43520	34 – 66	Neutral
		43521 – 65535	67 – 100	Cold

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 21 : Effects, 16 bit resolution per function

Para.	DMX Channel	Value	Percent	Function
Welding				
Preset: Ch3: 170-179				
Para.	DMX Channel	Value 16 bit	Percent	Function
1	5 (Hi) 6 (Lo)	0 – 65535	0 – 100	Speed
2	7 (Hi) 8 (Lo)	0 – 65535	0 – 100	Min Intensity Level
3	9 (Hi) 10 (Lo)	0 – 65535	0 – 100	Color Temp. (2700K~10000K)
4	11 (Hi) 12 (Lo)	Green / Magenta Adjustment		
		0~5000	0~7	neutral / no effect
		5001~10000	8~15	full minus green
		10001~29999	16~46	-99% --> -1%
		30000~40000	47~61	neutral / no effect
		40001~59999	62~92	1% --> 99%
60000~65535	93~100	full plus green		
5	13 (Hi) 14 (Lo)	0 – 65535	0 – 100	Color Change Coefficient White --> Color
6	15 (Hi) 16 (Lo)	0 – 65535	0 – 100	Adjust HUE (0~359)
7	17 (Hi) 18 (Lo)	0 – 65535	0 – 100	Adjust Saturation (0~100%)

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2 - 11	0 – 255	0 – 100	Color Parameter #1 ~ #10
12	Mode Selection		
	0 – 12	0 – 4	#1 CCT
	13 – 25	5 – 9	#2 HSI
	26 - 38	10 - 14	#3 RGBWW
	39 – 50	15 - 19	#4 x y Coordinate Mode
	51 - 63	20 - 24	#5 CCT / HSI
	64 - 76	25 - 29	#6 CCT / RGBWW
	77 - 89	30 - 34	#7 CCT / x y Coordinate Mode
	90 - 101	35 - 39	#8 GEL
	102 - 114	40 - 44	#9 Effect
115 - 255	45 - 100	Reserved for future use	
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#1 CCT Mode			
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Color Temp. (2700K~10000K)
3	Green / Magenta Adjustment		
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
245~255	97~100	full plus green	
12			Mode Selection
	0 – 12	0 – 4	#1 CCT
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#2 HSI Mode			
1	Master Intensity		
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Adjust HUE (0~359)
3	0 – 255	0 – 100	Adjust Saturation (0~100%)
12	Mode Selection		
	13 – 25	5 – 9	#2 H S I
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#3 RGBWW Mode			
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Adjust Red Color intensity
3	0 – 255	0 – 100	Adjust Green Color intensity
4	0 – 255	0 – 100	Adjust Blue Color intensity
5	0 – 255	0 – 100	Adjust Warm White Color intensity
6	0 – 255	0 – 100	Adjust Cold White Color intensity
12			Mode Selection
	26 - 38	10 - 14	#3 RGBWW
13			Fan control
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#4 x y Coordinate Mode			
1	Master Intensity		
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	x Coordinate (0.0 – 0.8)
3	0 – 255	0 – 100	y Coordinate (0.0 – 0.8)
12	Mode Selection		
	39 – 50	15 - 19	#4 x y Coordinate Mode
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#5 CCT/ HSI Mode			
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Color Temp. (2700K~10000K)
3			Green / Magenta Adjustment
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
245~255	97~100	full plus green	
4	0 – 255	0 – 100	Color Change Coefficient White --> Color
5	0 – 255	0 – 100	Adjust HUE (0~359)
6	0 – 255	0 – 100	Adjust Saturation (0~100%)
12			Mode Selection
	51 - 63	20 - 24	#5 CCT / HSI
13			Fan control
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#6 CCT / RGBWW Mode			
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Color Temp. (2700K~10000K)
3			Green / Magenta Adjustment
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
245~255	97~100	full plus green	
4	0 – 255	0 – 100	Color Change Coefficient White --> Color
5	0 – 255	0 – 100	Adjust Red Color intensity
6	0 – 255	0 – 100	Adjust Green Color intensity
7	0 – 255	0 – 100	Adjust Blue Color intensity
8	0 – 255	0 – 100	Adjust Warm White Color intensity
9	0 – 255	0 – 100	Adjust Cold White Color intensity
12			Mode Selection
	64 - 76	25 - 29	#6 CCT / RGBWW

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#7 CCT/ xy Coordinate Mode			
DMX Channel	Value 8 bit	Percent	Function
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2	0 – 255	0 – 100	Color Temp. (2700K~10000K)
3	Green / Magenta Adjustment		
	0~10	0~4	neutral / no effect
	11~20	5~8	full minus green
	21~119	9~46	-99% --> -1%
	120~145	47~57	neutral / no effect
	146~244	58~96	1% --> 99%
245~255	97~100	full plus green	
4	0 – 255	0 – 100	Color Change Coefficient White --> Color
5	0 – 255	0 – 100	x Coordinate (0.0 – 0.8)
6	0 – 255	0 – 100	y Coordinate (0.0 – 0,8)
12	Mode Selection		
	77 - 89	30 - 34	#7 CCT / x y Coordinate Mode
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#8 Gel Mode			
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2			CCT Selection
	0 – 127	0 – 50	3.200 K
	128 – 255	51 – 100	5.600 K
3			Filter Class
	0 – 12	0 – 4	CTB under Color Correction
	13 – 25	5 – 9	CTO under Color Correction
	26 – 38	10 – 14	CTS under Color Correction
	39 – 50	15 – 19	+/- Green under Color Correction
	51 – 61	20 – 24	Misc under Color Correction
	62 – 127	25 – 49	Reserved
	128 – 140	50 – 54	Red under Color Filter
	141 – 152	55 – 59	Orange under Color Filter
	153 – 165	60 – 64	Yellow under Color Filter
	166 – 178	65 – 69	Green under Color Filter
	179 – 191	70 – 74	Blue under Color Filter
	192 – 203	75 – 79	Purple under Color Filter
	204 – 255	80 – 100	Reserved
4	0 – 255	0 – 100	Filter Code (Please refer Mode 16 for detail filter code)
12			Mode Selection
	90 - 101	35 - 39	#8 GEL

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
13	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
#9 Effect Mode			
1			Master Intensity
	0 – 255	0 – 100	0 % (closed) → 100% (open)
2			Effect Selection
	0 – 9	0 – 4	No Effect
	10 – 19	5 – 7	Party
	20 – 29	8 – 11	Candle
	30 – 39	12 – 15	Clouds Passing
	40 – 49	16 – 19	Club
	50 – 59	20 – 23	Color Chase
	60 – 69	24 – 27	Explosion
	70 – 79	28 – 31	Fire
	80 – 89	32 – 35	Fireworks
	90 – 99	36 – 39	Flu.Flicker
	100 – 109	40 – 43	Lightning
	110 – 119	44 – 47	Paparazzi
	120 – 129	48 – 51	Police Car
	130 – 139	52 – 55	Process
	140 – 149	56 – 58	Pulsing
	150 – 159	59 – 62	Strobe
160 – 169	63 – 66	TV	
170 – 179	67 – 70	Welding	
180 - 255	71 - 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
3	0 – 255	0 – 100	Effect Parameter 1 (Please refer Mode 20 for detail setting)
4	0 – 255	0 – 100	Effect Parameter 2 (Please refer Mode 20 for detail setting)
5	0 – 255	0 – 100	Effect Parameter 3 (Please refer Mode 20 for detail setting)
6	0 – 255	0 – 100	Effect Parameter 4 (Please refer Mode 20 for detail setting)
7	0 – 255	0 – 100	Effect Parameter 5 (Please refer Mode 20 for detail setting)
8	0 – 255	0 – 100	Effect Parameter 6 (Please refer Mode 20 for detail setting)
9	0 – 255	0 – 100	Effect Parameter 7 (Please refer Mode 20 for detail setting)
10	0 – 255	0 – 100	Effect Parameter 8 (Please refer Mode 20 for detail setting)
11	0 – 255	0 – 100	Effect Parameter 9 (Please refer Mode 20 for detail setting)
12	Mode Selection		
	102 - 114	40 - 44	#9 Effect

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 22 :Ultimate DMX Protocol, 8 bit resolution per function

DMX Channel	Value	Percent	Function
13			Fan control
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)

3 ~ 22	0 – 65535	0 – 100	Color Parameter #1 - 10
--------	-----------	---------	-------------------------

23	Mode Selection		
	0 – 12	0 – 4	#1 CCT
	13 – 25	5 – 9	#2 HSI
	26 - 38	10 - 14	#3 RGBWW
	39 – 50	15 - 19	#4 x y Coordinate Mode
	51 - 63	20 - 24	#5 CCT / HSI
	64 - 76	25 - 29	#6 CCT / RGBWW
	77 - 89	30 - 34	#7 CCT / x y Coordinate Mode
	90 - 101	35 - 39	#8 GEL
	102 - 114	40 - 44	#9 Effect
115 - 255	45 - 100	Reserved for future use	

24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#1 CCT Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (Hi)	0 –65535	0 – 100	Color Temp. (2700K~10000K)
4 (Lo)			
5 (Hi)	Green / Magenta Adjustment		
6 (Lo)	0~5000	0~7	neutral / no effect
	5001~10000	8~15	full minus green
	10001~29999	16~46	-99% --> -1%
	30000~40000	47~61	neutral / no effect
	40001~59999	62~92	1% --> 99%
	60000~65535	93~100	full plus green
23	0 – 12	Mode Selection	
		0 – 4	#1 CCT
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#2 HSI Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (Hi)	0 – 65535	0 – 100	Adjust HUE (0~359)
4 (Lo)			
5 (Hi)	0 – 65535	0 – 100	Adjust Saturation (0~100%)
6 (Lo)			
23	Mode Selection		
	13 – 25	5 – 9	#2 H S I
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#3 RGBWW Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (Hi)	0 –65535	0 – 100	Adjust Red Color intensity
4 (Lo)			
5 (Hi)	0 –65535	0 – 100	Adjust Green Color intensity
6 (Lo)			
7 (Hi)	0 –65535	0 – 100	Adjust Blue Color intensity
8 (Lo)			
9 (Hi)	0 –65535	0 – 100	Adjust Warm White Color intensity
10 (Lo)			
11 (Hi)	0 –65535	0 – 100	Adjust Cold White Color intensity
12 (Lo)			
23	Mode Selection		
	26 - 38	10 - 14	#3 RGBWW
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#4 x y Coordinate Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (Hi)	0 – 65535	0 – 100	x Coordinate (0.0 – 0.8)
4 (Lo)			
5 (Hi)	0 – 65535	0 – 100	y Coordinate (0.0 – 0.8)
6 (Lo)			
23	Mode Selection		
	39 – 50	15 – 19	#4 x y Coordinate Mode
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 – 19	Quiet Mode
	50 – 99	20 – 39	Auto Mode
	100 – 150	40 – 59	Variable
	151 – 175	60 – 68	Full Speed
	176 – 200	69 – 78	Full Speed but Limited Output 80%
	201 – 225	79 – 88	Full Speed but Limited Output 60%
	226 – 249	89 – 97	Full Speed but Limited Output 40%
250 – 255	98 – 100	Reserved for future use	

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#5 CCT/ HSI Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (Hi)	0 –65535	0 – 100	Color Temp. (2700K~10000K)
4 (Lo)			
5 (Hi)	Green / Magenta Adjustment		
6 (Lo)	0~5000	0~7	neutral / no effect
	5001~10000	8~15	full minus green
	10001~29999	16~46	-99% --> -1%
	30000~40000	47~61	neutral / no effect
	40001~59999	62~92	1% --> 99%
	60000~65535	93~100	full plus green
7 (Hi)	0 –65535	0 – 100	Color Change Coefficient White --> Color
8 (Lo)			
9 (Hi)	0 –65535	0 – 100	Adjust HUE (0~359)
10 (Lo)			
11 (Hi)	0 –65535	0 – 100	Adjust Saturation (0~100%)
12 (Lo)			
23	Mode Selection		
	51 - 63	20 - 24	#5 CCT / HSI
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#6 CCT / RGBWW Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (Hi)	0 –65535	0 – 100	Color Temp. (2700K~10000K)
4 (Lo)			
5 (Hi)	Green / Magenta Adjustment		
6 (Lo)	0~5000	0~7	neutral / no effect
	5001~10000	8~15	full minus green
	10001~29999	16~46	-99% --> -1%
	30000~40000	47~61	neutral / no effect
	40001~59999	62~92	1% --> 99%
	60000~65535	93~100	full plus green
7 (Hi)	0 –65535	0 – 100	Color Change Coefficient White --> Color
8 (Lo)			
9 (Hi)	0 –65535	0 – 100	Adjust Red Color intensity
10 (Lo)			
11 (Hi)	0 –65535	0 – 100	Adjust Green Color intensity
12 (Lo)			
13 (Hi)	0 –65535	0 – 100	Adjust Blue Color intensity
14 (Lo)			
15 (Hi)	0 –65535	0 – 100	Adjust Warm White Color intensity
16 (Lo)			
17 (Hi)	0 –65535	0 – 100	Adjust Cold White Color intensity
18 (Lo)			
23	Mode Selection		
	64 - 76	25 - 29	#6 CCT / RGBWW

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID: Aurora V1 200C 0x0202
 Aurora V1 400C 0x0201
 Aurora V2 220C 0x0211
 Aurora V2 450C 0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#7 CCT/ xy Coordinate Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3 (Hi)	0 –65535	0 – 100	Color Temp. (2700K~10000K)
4 (Lo)			
5 (Hi)	Green / Magenta Adjustment		
6 (Lo)	0~5000	0~7	neutral / no effect
	5001~10000	8~15	full minus green
	10001~29999	16~46	-99% --> -1%
	30000~40000	47~61	neutral / no effect
	40001~59999	62~92	1% --> 99%
	60000~65535	93~100	full plus green
7 (Hi)	0 –65535	0 – 100	Color Change Coefficient
8 (Lo)			White --> Color
9 (Hi)	0 –65535	0 – 100	x Coordinate (0.0 – 0.8)
10 (Lo)			
11 (Hi)	0 –65535	0 – 100	y Coordinate (0.0 – 0,8)
12 (Lo)			
23	Mode Selection		
	77 - 89	30 - 34	#7 CCT / x y Coordinate Mode
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#8 Gel Mode			
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
CCT Selection			
3 (Hi)	CCT Selection		
4 (Lo)	0- 32767	0 – 50	3.200 K
	32768 - 65535	51 – 100	5.600 K
Filter Class			
5 (Hi)	Filter Class		
6 (Lo)	0 – 3327	0 – 4	CTB under Color Correction
	3328 – 6555	5 – 9	CTO under Color Correction
	6556 – 9983	10 – 14	CTS under Color Correction
	9984 – 13055	15 – 19	+/- Green under Color Correction
	13056 – 15871	20 – 24	Misc under Color Correction
	15872 – 32767	25 – 49	Reserved
	32768 – 36095	50 – 54	Red under Color Filter
	36096 – 39167	55 – 59	Orange under Color Filter
	39168 – 42495	60 – 64	Yellow under Color Filter
	42496 – 45823	65 – 69	Green under Color Filter
	45824 – 49151	70 – 74	Blue under Color Filter
	49152 – 52223	75 – 79	Purple under Color Filter
	52224 – 65535	80 –100	Reserved
Filter Code (Please refer Mode 17 for detail filter code)			
7 (Hi)	0 – 65535	0 – 100	Filter Code (Please refer Mode 17 for detail filter code)
8 (Lo)			
Mode Selection			
23	90 - 101	35 - 39	#8 GEL
Fan control			
24	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
#9 Effect Mode			
DMX Channel	Value 8/16 bit	Percent	Function
1 (Hi)	Master Intensity		
2 (Lo)	0 – 65535	0 – 100	0 % (closed) → 100% (open)
3	Effect Selection		
	0 – 9	0 – 4	No Effect
	10 – 19	5 – 7	Party
	20 – 29	8 – 11	Candle
	30 – 39	12 – 15	Clouds Passing
	40 – 49	16 – 19	Club
	50 – 59	20 – 23	Color Chase
	60 – 69	24 – 27	Explosion
	70 – 79	28 – 31	Fire
	80 – 89	32 – 35	Fireworks
	90 – 99	36 – 39	Flu.Flicker
	100 – 109	40 – 43	Lightning
	110 – 119	44 – 47	Paparazzi
	120 – 129	48 – 51	Police Car
	130 – 139	52 – 55	Process
	140 – 149	56 – 58	Pulsing
	150 – 159	59 – 62	Strobe
160 – 169	63 – 66	TV	
170 – 179	67 – 70	Welding	
180 - 255	71 - 100	Reserved for future use	
4			Reserved for future use

Filmgear LED Lights DMX Chart for Aurora RGB Panel

V1.7.4 or +

Manufacture ID: 0x4142

Model ID:	Aurora V1 200C	0x0202
	Aurora V1 400C	0x0201
	Aurora V2 220C	0x0211
	Aurora V2 450C	0x0212

Mode 23 :Ultimate DMX Protocol, 16 bit resolution per function

DMX Channel	Value	Percent	Function
5 (Hi)	Effect Parameter #1		
6 (Lo)	0 – 65535	0 – 100	Para#1 (Please refer Mode 21 for detail setting)
7 (Hi)	Effect Parameter #2		
8 (Lo)	0 – 65535	0 – 100	Para #2 (Please refer Mode 21 for detail setting)
9 (Hi)	Effect Parameter #3		
10 (Lo)	0 – 65535	0 – 100	Para #3 (Please refer Mode 21 for detail setting)
11 (Hi)	Effect Parameter #4		
12 (Lo)	0 – 65535	0 – 100	Para #4 (Please refer Mode 21 for detail setting)
13 (Hi)	Effect Parameter #5		
14 (Lo)	0 – 65535	0 – 100	Para #5 (Please refer Mode 21 for detail setting)
15 (Hi)	Effect Parameter #6		
16 (Lo)	0 – 65535	0 – 100	Para #6 (Please refer Mode 21 for detail setting)
17 (Hi)	Effect Parameter #7		
18 (Lo)	0 – 65535	0 – 100	Para #7 (Please refer Mode 21 for detail setting)
19 (Hi)	Effect Parameter #8		
20 (Lo)	0 – 65535	0 – 100	Para #8 (Please refer Mode 21 for detail setting)
21 (Hi)	Effect Parameter #9		
22 (Lo)	0 – 65535	0 – 100	Para #9 (Please refer Mode 21 for detail setting)
23	Mode Selection		
	102 - 114	40 - 44	#9 Effect
24	Fan control		
	0 – 9	0 – 3	As Fixture Setting
	10 – 49	4 - 19	Quiet Mode
	50 – 99	20 - 39	Auto Mode
	100 - 150	40 - 59	Variable
	151 – 175	60 – 68	Full Speed
	176 - 200	69 – 78	Full Speed but Limited Output 80%
	201 - 225	79 – 88	Full Speed but Limited Output 60%
	226 - 249	89 – 97	Full Speed but Limited Output 40%
	250 – 255	98 – 100	Reserved for future use